


## LED Floor Lamp Operation Instruction



### 1. Parts List –

LED Floor Lamp x 1

USB-C Charging Cable x 1


User **Operation Instruction** x 1

### 2. Specification –

- 1) Material: plastic + metal
- 2) Water resistance of LED lights: IP44
- 3) Colors: Warm White (100% & 20% Level) & RGB LED Color Options (smooth changing mode, single color mode)
- 4) Light battery: Built-in rechargeable battery
- 5) Charging time: 5 hours via USB; full day under good sunlight
- 6) Battery autonomy (for information only): 6 hours at full brightness (100%)
- 7) RGB colors (multicolor): 20 hours
- 8) Charger voltage: 5V/2A or 5V/1A
- 9) Solar panel: 1.5W
- 10) Color change – warm white in 2 levels
- 11) Rechargeable, convenient for charging by USB-C cable and solar

### 3. How to assemble –

Assemble the lamp shape with the pole & bottom as shown below.



#### Assembly Steps

**Step 1:** Place the base on stable ground, first install the lower pole with the base.

**Step 2-3:** Install the 3 poles in the middle.

**Step 4:** Install the top pole and the lampshade together.

**Step 5:** Connect the top pole with the middle poles.

### 4. Operating by pulling the switch on the light shade's bottom

1st short pull, to get into Warm white 100% brightness

2nd short pull, to get into Warm white 20% brightness

3rd short pull, to get into RGB multi-color mode, smooth changing

4th short pull, to get into RGB single color mode, stay at any one color from the last smooth change

5th short pull, to turn off the light

## 5. Battery Charging

***Suggest charging the lamp by connecting the USB-C cable for 6-8 hours at first use.***

Charge the light using the provided USB-C cable, compatible with any computer or cell phone, or a 5V/1A or 5V/2A wall charger.

- 1) Connect the USB-A charging head to a USB Charger or a USB port on the computer.
- 3) Insert the USB-C charging head into the Type-C port on the lamp (under the light shade).
- 4) When the charging indicator light turns green, it indicates that it is fully charged.
- 5) Cover the water-resistant rubber cap tightly after it is fully charged.

